

N-E Color Drape



USER MANUAL

Table of Contents

Safety Information.....	3
Specifications.....	4
Main Power Connection.....	5
DMX-512 Connection.....	5
Installation.....	6
Rigging the Fixture.....	6
Main Control Menu.....	7
DMX Profile.....	8
Cleaning & Maintenance.....	10
Parts List.....	10

Check that the unit has not been damaged during transport



Read all cautions and warnings
prior to operation of this
equipment

Protection Against Fire



Fire

1. Maintain a minimum of 2 foot distance from any type of flame.
3. Replace fuse only with the specified type and rating.
4. Do Not install the unit too close to a heat source.
5. Make sure cables are properly secured away from unit movement.
6. Maximum surface operating temperature 80°.

Protection Against Fire



Electrical

1. Disconnect power before servicing.
2. For connection to main power supply proceed to page 5.
3. This unit must be earthed. (electronically grounded)
4. Do not expose unit to rain or moisture.

Protection Against Mechanical Hazards



Mechanical

1. Use safety chain when hanging unit.
2. Secure the plastic cover when hanging the light on ceiling.
3. Use quality clamps or bolts when positioning unit
4. Do not open unit while it is on, risk of electrical shock.

Specifications

Part Numbers

Fixture


4122-N-E Color Drape

Accessories

9057-N-E Color Drape Road Case

Drape Specifications

- LED Quantity:** 128
- LED Type:** Tri Chip
- LED Watts:** .20 X3 R,G,B
- Effects:** RGB color mixing
Strobe
Bright burst effect
Auto-programs
- Signal Connection:** 5-pin XLR connectors (cable included)
- LED Viewing Angle:** 115° (± 5°)
- Fastening System:** Velcro jointer and hanging grommets



Fixture	Packaged for Shipping
Size: 19 feet 8 inch H x 13 feet 1 inch L x 2 inch W	Size: 30"L x 18"W x 10"H
Weight: 36 lb	Weight: 40lbs

Driver Specifications (included)

- Control Quantity:** Control 1 N-E Color Drape
- Protocol:** DMX 512
- DMX Channels:**

Mode A	3 DMX Channels	Dimmer, Macro, Macro Speed
Mode P	24 DMX Channels	R,G,B X 8
Mode F	32 DMX Channels	Dimmer/ Strobe, R,G,B X 8
- DMX Connection:** Neutrik 3 Pin XLR Input & output
- Curtain Connection:** Neutrik 5 Pin XLR output
- Power Connection:** Neutrik Power Con input (included)
- Ballast:** Electronic
- Watts:** 19
- Amps:** .30




Main Power Connection

Caution!


1. Do not connect fixture to a dimmer system.
2. This unit has Auto switching power supply. It will respond to 110V or 220V automatically
3. This unit must be earthed. (electronically grounded)
4. Replace fuse only with the specified type and rating.


The occupation of the connection-cable is as follows:

110V Connection

Cable (USA)	Cable (EU)	Pin	Connection
Black	Brown	Live	L
White	Light Blue	Neutral	N
Green	Yellow/Green	Ground	

220V Connection


Cable (USA)	Cable (EU)	Pin	Connection
Black	Brown	Live	L
White	Light Blue	Live	N
Green	Yellow/Green	Neutral	



DMX-512 Connection


The fixture is equipped with 3 pin XLR Sockets for DMX input and output. The sockets are wired in parallel. Only use a shielded twisted pair cable designed for RS-485 and 3 pin XLR plugs and connectors in order to connect the controller with the fixture or the fixture with another.

DMX—input



1. Shield
2. Signal (-)
3. Signal (+)


DMX—output



Caution!

At the last fixture the DMX signal needs to be terminated with a terminator. Solder a 120 Ohm resistor between the (-) and the (+) signal into a 3 pin XLR plug and plug it in to the last fixture on the signal run. Pre-manufactured terminator plugs are available for purchase from your Mega-Lite dealer (HOS-DMXT).

Installation



Rigging the fixture

Caution!


1. The installations must be carried out by an authorized dealer or trained professional.
2. Unit may cause severe injuries if you have doubts concerning the safety do not install.
3. Unit is to be 24 inches away from flammable materials (decoration material)
4. Use high quality installation equipment to hang unit.

When rigging a unit it is very important that you follow common safety procedures. Rigging requires extensive experience including but not limited to calculating working loads, material being used and periodic safety inspections. If you lack these qualifications, do not attempt the installation yourself, instead use a professional structural rigger.

When rigging the unit always be secured with a secondary safety attachment. The installation location of the projector has got to be built in the way that it can hold 10 times the weight for 1 hour with out any harming. Installation should be checked at least one time a year by a skilled person.

Main Control Menu

The control board on the fixture base is your interface to access and control all the functions on the unit. Its digital display gives you a code view of the options. The following will explain each function and its options.



Press the **Menu** button, Use the **up/down** keys to select the required function Press **Enter** to select

Addr DMX Modes

Use the **Enter** keys to select the required DMX Mode. Repress **Enter** to scroll to the mode options **A,P** and **F**. Use the **up/down** keys to select the required DMX channel. Press **Menu** to confirm.

RL -- Red LED Intensity

Use the **Enter** keys to select the required intensity of the red LED. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

GL -- Green LED Intensity

Use the **Enter** keys to select the required intensity of the green LED. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

BL -- Blue LED Intensity

Use the **Enter** keys to select the required intensity of the blue LED. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

FLAS Strobe LED Speed

Use the **Enter** keys to select the required speed of strobe. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

FADE Fade Color LED Speed

Use the **Enter** keys to select the required speed of fade color. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

ASC - Snap Color LED Speed

Use the **Enter** keys to select the required speed of snap color. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

CE-- Macro Effects

Use the **Enter** keys to select the required macro effect. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

CS-- Macro Speed

Use the **Enter** keys to select the required speed of the macro effect. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

SOUR Sound Macro Color

Use the **Enter** keys to select the required sound macro effect. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

SOUF Sound Macro Flash

Use the **Enter** keys to select the required sound flash macro effect. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

SENS Sound Sensor Sensitivity

Use the **Enter** keys to select the required sound sensor sensitivity. Use the **up/down** keys to select options from 1 to 15. Press **Menu** to confirm.

DMX Profile

N-E Color Drape Mode A (3 Channel)

DMX Chanel	Function	Description	Value		
1	Dimmer	LED intensity	0-255		
		Color Fade	0-15		
		Color Pulse	16-31		
		Random Fade	32-47		
		Color Snap	48-63		
		RGBW S	64-79		
		Color Snap + White Strobe	80-95		
		2	Macro Effect	White Snap + Color Strobe	96-111
				RGB Snap +White Strobe	112-127
				RGBCMY Snap + White Strobe	128-143
		CMY Snap + White Strobe	144-159		
		CMY Snap + White Strobe	160-175		
		RGBCMYW Snap	176-191		
		RGBWCMY Snap	192-207		
		RGB Snap White Strobe	208-223		
3	Effect Speed	Star Effect	224-239		
		Star Effect 2	240-255		
		Speed of Effect Macro	0-255		

N-E Color Drape Mode P (24 Channel)

DMX Chanel	Function	Description	Value
1	LED Color	Red LED intensity	0-255
2	LED Color	Green LED Intensity	0-255
3	LED Color	Blue LED Intensity	0-255
" "	" "	" "	" "
22	LED Color	Red LED intensity	0-255
23	LED Color	Green LED Intensity	0-255
24	LED Color	Blue LED Intensity	0-255

N-E Color Drape Mode F (32 Channel)

DMX Chanel	Function	Description	Value
1	Dimmer	Dimmer	0-152
		Strobe (slow to fast)	153-242
		Dimmer Full On	243-255
2	LED Color	Red LED intensity	0-255
3	LED Color	Green LED Intensity	0-255
4	LED Color	Blue LED Intensity	0-255
" "	" "	" "	" "
29	Dimmer	Dimmer	0-152
		Strobe (slow to fast)	153-242
		Dimmer Full On	243-255
30	LED Color	Red LED intensity	0-255
31	LED Color	Green LED Intensity	0-255
32	LED Color	Blue LED Intensity	0-255

Cleaning and maintenance

Installation Maintenance: The operator has to make sure that the unit is operating safely and has the installations and electronics checked by an expert every 2 years.

The following points have to be considered during the inspection:

- 1) All screws used for installing the device or part of the device have to be tightly connected and must not be corroded.
- 2) There must not be any deformations on the housing, fixation and installation spots (ceiling, suspension, trussing).
- 3) The electronic power supply cables must not show any damages, material fatigue (e.g. porous cables) or sediments. Further instructions depending on the installation spot and usage have to be adhered by a skilled installer and any safety problems have to be removed.

Disconnect from mains before starting maintenance operation!



Caution Danger to life!

Electrical

We recommend a frequent cleaning of the device. Please use lint free soft brush!

- 1) The drape will require periodic cleaning on usage and environment. Environment with foggers will require more periodic cleaning as fog fluid tends to build up residues, reducing the light output.
- 2) The drape fixture should be cleaned using a vacuum hose.

Note: There is no serviceable parts inside the device except for the LED's. Maintenance and service operations are to be carried out by authorized dealers.

Replacing the fuse: Only replace the fuse with the same type and rating.

Replacing the power cable: If the power cable of this device becomes damaged, it has to be replaced by authorized dealers only in order to avoid hazards.

Should you have further questions , please contact your dealer.

Parts List

4122-case	N-E Color Drape Road Case
4122-driver	N-E Color Drape Driver
4122-pcb+dis	Main PCB Card
4122-ps	Power Supply
4122-rec	Receiver Card
4000-fh	Fuse Holder
4122-led	Tri LED



Mega-Lite
5718 Kenwick St
San Antonio, TX 78238
Ph 210-684-2600 Fax 210-855-6279
www.mega-lite.com / info@mega-lite.com